

START ▶ CONTROL Tones [ON 9]

[Note: if Agenda includes QWA Procedure–give 1-2 min for STNS to do work–“standby”...]

“CONTROL ON 9; [“Monitoring Check activated”] [“Sit Rep activated use FMT T9A OR T9M”] ...

▼ [“Conduct QWA Procedure”] [“ QWA Not requested”] [ETC...]
 [FIRE NET–USE FIRE NET SCRIPT] [MOBILE EVAC – USE MOBILE EVAC SCRIPT]

“STAND BY” ▶ ▶ ▶ ▶

▼ IF TACTICALS
 “NEED MAPPING” , ETC.

<p>IF have 55 and / or 57 relay ▼ “NEED <u>55 RELAY</u> <u>57 RELAY</u> ...” [F 8, B1, ETC...] ... “ TONE, ANNOUNCE, SECURE RPTS, RPT BACK WHEN DONE” ... “COPY”</p>
--

[CONTROL CONTINUING ON 9]

<p>▶ “CONTROL ON 9, TAKING REPORTS by AREA [NOTE CONTROL AND MAPPING (IF ACTIVATED) RECORDS ALL REPORTS ON 9] Village Report: “FIRST STN ...” ...”F1” ... “F1 GO” ...“COPY F1”. .. “NEXT” ... MIDWAY REPORT ... LONG HOLLOW REPORT ANY OTHERS, RELAYS, LATE OR MISSED.]</p>
--

<p>[IF ANOTHER STN IS 55 57 RELAY, CONTROL CONTINUES ON 9]</p>

OR

<p>[IF CONTROL ACTING ALONE, CONTROL WILL ALSO ACT AS 55 / 57 RELAYS] “ SAY ON 9: “STAND BY” “QSY 55 [57] CONTROL OUT”</p>

[reports from 9]

<p>CONTROL DOES BELOW ON 9</p>	<p>[STN ACTING AS 55 RELAY 57 RELAY DOES BELOW] RELAYS ON 55 / 57 [AS APPLIES] [BELOW] 55/57 NEEDS 2 RADIOS (ONE FOR 9 (TO HEAR CONTROL) & ONE FOR 55 /57)</p>
<p style="text-align: center;">↓</p> <p>[CONTROL TAKES IN ALL RPTS ON 9 FROM 9, 55, 57 ETC...]</p> <p style="text-align: center;">↓</p> <p>[REPORTS from 9]</p> <p style="text-align: center;">↓</p> <p>[CONTROL RESPONSE ON 9] “ 55 AND 57 RELAYS GO”... →</p> <p>[REPORTS taken from 55 57]</p> <p>[CONTROL RESPONSE ON 9] “COPY”... →</p>	<p>2 TONES [ON 55] SAY “ <u>55 RELAY</u> ON 55” [ON 57] SAY [“ <u>57 RELAY</u> ON 57”]</p> <p>“[MONITORING CHECK ACTIVATED] [SIT REP ACTIVATED T9A T9M] [CONDUCT QWA PROC.] ETC ... [QWA NOT REQUESTED] ETC... “STAND BY”... “TAKING RPTS BY AREA” [RECORD REPORTS] “SITES REPORT...“FIRST STN ...” “COPY SITES 7” ... “NEXT”... “REST AREA REPORT ...“FIRST STN ...” “NEXT”... “WILSON HILL REPORT ...“FIRST STN...” NEXT”... “ANY OTHERS, RELAYS, LATE OR MISSED”... “STANDBY FOR <u>NET SUMMARY REPORT</u> AND <u>CONTROL RECOMMENDATION</u> FROM PRIMARY NET” [NOTE: THIS MUST BE OBTAINED FROM CONTROL ON 9] [IF APPLICABLE] “DUPLICATING ON 57” [55] “QSY 57 [55]” [55 RELAY] [57 RELAY] OUT [THEN ID] EG., [ID / K6PDS]”</p> <p>[NOTE: AFTER 55 / 57 TAKES ALL REPORTS, GO TO 9 AND GIVE REPORTS TO CONTROL. ON 9. TO BE DONE EVEN IF CONTROL IS ALSO 55 57 RELAYS SO ALL STNS HEAR!]</p> <p>← [RELAY SAY ON 9] “<u>CONTROL</u> , <u>55 RELAY 57 RELAY</u> ON 9”..</p> <p>← [RELAY SAY ON 9 – EXAMPLE “ REPORT...” “4 AREAS REPORTING WILSON HILL 1 STN ALL QTH B QXA QWA SITES 2 STNS ALL QTH B QXA QWA REST AREA 1 STN ALL QTH B QXA QWA PINE RIDGE 1STN ALL QTH B QXA QWA ” END REPORT”</p>

[NOTE: CONTROL AND [MAPPING] TAKES ALL INPUT FROM 9, 55, 57 ... AND GENERATES]:

NET SUMMARY REPORT

CONTROL RECOMMENDATION

[NOTE: CONTROL MUST WAIT FOR ALL REPORTS FROM 9, 55, 57 BEFORE MAKING NET SUMMARY REPORT AND CONTROL RECOMMENDATION].

[# of stations reporting is stated to establish confidence level for Area]

SAY (EXAMPLE)

NET SUMMARY REPORT

7 AREAS reporting

VL 10 STNS ALL QXA QWA
LH 1 STN ALL QXA QWA
MW 3 STNS ALL QXA QWA
PR 1 STN ALL QXA QWA
WH 1 STN ALL QXA QWA
SITES 2 STNS ALL QXA QWA
RA 1 STN ALL QXA QWA

SAY "Any Stn disagree? ...

SAY (EXAMPLE)

CONTROL RECOMMENDATION

"No Action" [Other]

SAY "Any Stn disagree? ...

SAY "55 57 relays , CONTROL ON 9"

SAY "TX NET SUMMARY REPORT,
CONTROL RECOMMENDATION,
Deactivate, RPT when done"...

[NOTE: IF CONTROL ALONE,

Say "Control on 9, standby for 55 57 relay actions"..[then QSY 55 57]

OR

[OR, IF CONTROL IS WAITING FOR 55 57 RELAY STN TO DO ITS WORK,

CONTROL STAYS ON 9 AND SAYS

"CONTROL STANDING BY"

[NOTE: CONTROL MUST WAIT FOR 55 57 DEACTIVATION RESPONSE BEFORE CLOSING NET]

... [RESPONSE BY CONTROL ON 9]

SAY "GO"

SAY ... "copy"

THEN SAY "CONTROL ON 9"

[DEACTIVATE ANY TACTICALS

E.G., "MAPPING DEACTIVATE ...]

["MONITORING CHECK DEACTIVATED"]

["SIT REP DEACTIVATED", ETC...]"

"QSY SCAN" "

[F1 / IDENTIFIER] OUT"

[Note: 55 57 relay must listen to Control on 9 and record the NET SUMMARY REPORT AND CONTROL RECOMMENDATION

To be able to transmit to those on 55 57]

SAY "GO"

[55 / 57 relay responds ON 9] "COPY" ...

[SAY ON 55/57] "55 RELAY ON 55" ["57 RELAY ON 57"]

"NET SUMMARY REPORT" (# OF STNS NOT REPEATED ONLY AREAS)

E.G., "7 AREAS REPORTING

VILLAGE, LONGHOLLOW, MIDWAY, PINE RIDGE, WILSON HILL, SITES, REST AREA;

ALL STNS AND AREAS QXA AND QWA, NO EXCEPTIONS."

"CONTROL RECOMMENDATION:"

E.G., "NO ACTION" "ANY STN COPY?..."

"DUPLICATING ON 57 [ON 55]"

"55 RELAY [57 RELAY] DEACTIVATED [ID/K6PDS]"

[RELAY SAY ON 9] SAY .., "CONTROL, 55 57 RELAY ON 9"
[NOTE: THIS IS TO BE DONE EVEN IF CONTROL IS ALSO 55 57 RELAYS]

[RELAY SAY ON 9] SAY "TX OF NET SUMMARY REPORT AND CONTROL RECOMMENDATION DONE.

55 57 RELAY DEACTIVATED. OUT"

[NOTE: THIS IS TO BE DONE EVEN IF CONTROL IS ALSO 55 57 RELAYS]